

Pioneer Dj



DJM-350 2-channel DJ mixer with USB recording

USB Port for instant recording / 4 Innovative Effects: Filter, Crush, Jet and Gate / 3-band Equalising Isolator on each channel / High quality sound from isolated components / Mic / Aux Terminals / Cross Fader Curve Adjust / Track Mark button splits recording for indexed mixes



The new DJM-350 fuses innovative effects, high quality components and USB recording in a robust, DJ friendly design.

DJM-350 Specifications

No. of Channels:	2
Input Terminals:	CD / LINE × 2 (RCA) PHONO × 2 (RCA) MIC × 1 (1/4 inch PHONE × 1) AUX × 1 (RCA)
Output Terminals:	MASTER OUT × 1 (RCA × 1) HEADPHONE MONITOR OUT × 1 (1/4 inch PHONE) REC OUT × 1 (RCA)
Other Terminals:	Control Out × 2 (3.5mm mini-jack), USB A Port × 1
A/D, D/A Converter:	48 kHz/24-bit
Frequency Performance:	20 Hz–20 kHz
Total Harmonic Distortion:	0.007% or less
Signal/Noise Ratio:	97 dB (line)
Power Supply:	AC 220 ~ 240V (50 Hz/60 Hz)
Power Consumption:	18 W
Max External Dimensions:	218 × 301.1 × 106.6 mm (W×D×H)
Weight:	3.2 kg



Pioneer Europe N.V. Multimedia Division, Slough SL2 4QP, UK TEL +44 (0) 1753 789789

Features and specifications of the products described or illustrated in this catalogue are correct at the time of printing but could change as production changes might occur. This catalogue may contain typographical errors and the colours of the depicted products may deviate slightly from reality. Consult your Pioneer dealer to ensure that actual features and specifications match your requirements. This catalogue may contain references to products that may or will not be available in your country.

Designed and produced by Planet Interactive Arts Limited, www.planet-ia.com DJM-350-2PP-PEE

videos on
DJSOUNDS.COM